## **GUJARAT TECHNOLOGICAL UNIVERSITY** B. E. - SEMESTER – VII • EXAMINATION – WINTER 2012

Subject code: 172007 Subject Name: Modern Control System Time: 10.30 am - 01.00 pm Instructions:

1. Attempt any five questions.

2. Make suitable assumptions wherever necessary.

3. Figures to the right indicate full marks.

Q.1 (a) Consider a Unity-feedback type-2 system with open loop transfer function. 07

$$G(s) = \frac{k}{s^2}$$

It is desired to compensate the system so as to meet the following transient response

specification

Settling time,  $ts \le 4 \sec \theta$ 

Peak Overshoot for step input  $\leq 20\%$ 

- (b) Describe the steps required to design the cascade lag compensator for the reshaping of root locus.
- Q.2 (a) Consider a type-I unity feedback system with an open-loop transfer function. 07

$$G(s) = \frac{k}{s(s+1)}$$

It is desired to have the velocity error constant  $k_v = 10$ 

Phase Margin of the system be at least  $45^{\circ}$ .

- Design a suitable cascade Lead compensator the above system.
- (b) Consider a unity feedback system with plant transfer function is given by

$$G(s) = \frac{k}{s(s+2)}$$

It is desired to have the Phase margin  $\ge 60^{\circ}$  and

 $K_v \geq 10$ .

Design a suitable cascade Lag compensator for the above system.

(b) Consider a plant with transfer function

 $G(s) = \frac{4}{s(s+0.5)}$ 

Design a lead compensator system to meet the following specifications:

Damping ratio, 
$$\zeta = 0.5$$

Undamped natural frequency,  $\omega n = 5 \text{ rad/sec.}$ 

Q.3 (a) Obtain the state transition matrix of the following system

$$\dot{X} = \begin{pmatrix} 0 & 1 \\ -6 & -5 \end{pmatrix} \dot{x} + \begin{bmatrix} 0 \\ 1 \end{bmatrix} u$$
And y=[1 0]x

(b) Obtain the transfer function of the given state equation.

07

07

07

07

07

Date: 28/12/2012

**Total Marks: 70** 

2

$$\begin{bmatrix} \dot{x}_{1} \\ \dot{x}_{2} \\ \dot{x}_{3} \end{bmatrix} = \begin{bmatrix} 0 & 1 & 0 \\ -1 & -1 & 0 \\ 1 & 0 & 0 \end{bmatrix} \begin{bmatrix} x_{1} \\ x_{2} \\ x_{3} \end{bmatrix} + \begin{bmatrix} 0 \\ 1 \\ 0 \end{bmatrix} u$$
$$Y = \begin{bmatrix} 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} x_{1} \\ x_{2} \\ x_{3} \end{bmatrix}$$
$$OR$$

$$A = \begin{pmatrix} -3 & 1 \\ 0 & -1 \end{pmatrix}, B = \begin{bmatrix} 1 \\ 1 \end{bmatrix},$$
  
C=[1 1] and D=0

$$\dot{x} = \begin{pmatrix} -1 & 0 & 0 \\ 0 & -2 & 0 \\ 0 & 0 & -3 \end{pmatrix} x(t) + \begin{bmatrix} 1 \\ 1 \\ 0 \end{bmatrix} u$$
$$Y = \begin{bmatrix} 1 & 0 & 2 \end{bmatrix} x(t)$$

Test for controllability and Observability.

Q.4 (a) Define the Properties of z-transform and find the z-transform of the following 07 function.

(i) 
$$f(t) = t$$

(ii) 
$$f(t) = \sin wt$$

(iii) 
$$f(t) = e^{-at} \cos wt$$
.

(b) Explain the procedure to find stability of a sampled data control system using 07 jury's stability criterion.

OR

- Q.4 (a) Explain the stability analysis of sampled Data control system.
   Q.4 (b) Find the inverse z-transform of the following function.
   Q.7 (d) 07
- **Q.4** (b) Find the inverse z-transform of the following function. 0.5z

(i) 
$$F(z) = \frac{\cos z}{(z-1)^2}$$
  
(ii)  $F(z) = \frac{z}{(z+1)(z+2)}$ 

**Q.5** (a) A regulator system has plant  $\dot{x} = \begin{pmatrix} 0 & 1 \\ 20.6 & 0 \end{pmatrix} x + \begin{bmatrix} 0 \\ 1 \end{bmatrix} u$ 

Design a control law u= -kx. So that the closed-loop system has eigenvalues at -1.8  $\pm$  j2.4. (b) Explain the pole placement technique using control using state feedback controller. 07

Q.5 (a) Explain the methods used for solution of state equation. 07

(b) Derive the condition for controllability and Observability. 07

07

07

07